

This application is submitted in the name of the following inventor(s):

<u>Inventor</u>	<u>Citizenship</u>	<u>Residence City and State</u>
Subir VARMA	United States	San Jose, CA
Jean FUENTES	United States	Santa Clara, CA
Khuong NGO	United States	San Jose, CA
Paul TRUONG	United States	San Jose, CA
Reza MAJIDI-AHY	United States	Los Altos, CA

The assignee is Aperto Networks, Inc., a corporation having an office at
1637 South Main Street, Milpitas, California.

Title of the Invention

Adaptive Link Layer for Point to Multipoint Communication System

Background of the Invention

This application hereby incorporates by reference and claims benefit of U.S.
Application No. 09/475,642, filed 12/30/99 (Attorney Docket No. 164.1002.01).

1. Field of the Invention

1
2 This invention relates to a link layer, such as for use in a wireless communi-
3 cation system.

4
5 2. *Related Art*

6
7 Wireless communication between a sender and a receiver includes sending
8 information using a wireless communication link, in which the sender modulates infor-
9 mation onto a wireless communication channel (such as a frequency band reserved for
10 wireless communication between the sender and the receiver). The receiver demodulates
11 that information from the wireless communication channel, so as to recover the original
12 information.

13
14 One problem with known systems is that physical characteristics of the
15 communication link between the sender and receiver can change substantially over rela-
16 tively short periods of time. For example, the distance between the sender and receiver
17 can change. In a second example, the equipment used by the sender or receiver (that is
18 the consumer premises equipment) can change. Moreover, these physical characteristics
19 can change independently of each other. As a result, selection of a single set of such
20 physical characteristics can result in relatively ineffective or inefficient communication
21 between the sender and the receiver.

novel and non-obvious in view of the known art. Examples described below primarily relate to a wireless communication system, but the invention is broadly applicable to many different types of communication in which characteristics of the communication link are subject to change.

Brief Description of the Drawings

Figure 1 shows a block diagram of a system using a new wireless transport layer in a wireless communication system.

Figure 2 shows a timing diagram of a TDMA frame using a new wireless transport layer in a wireless communication system.

Figure 3 shows a process flow diagram of a method for operating a system using a new wireless transport layer in a wireless communication system.

Detailed Description of the Preferred Embodiment

In the following description, a preferred embodiment of the invention is described with regard to preferred process steps and data structures. Embodiments of the invention can be implemented using general-purpose processors or special purpose processors operating under program control, or other circuits, adapted to particular process

steps and data structures described herein. Implementation of the process steps and data structures described herein would not require undue experimentation or further invention.

Related Application

Inventions described herein can be used in conjunction with inventions described in the following documents.

- U.S. Patent Application Serial No. _____, Express Mail Mailing No. _____, filed **the same day** in the name of **the same inventors**, attorney docket number 164.1003.01, titled “Adaptive Point to Multipoint Communication System.”

Each of these documents is hereby incorporated by reference as if fully set forth herein.

Lexicography

The following terms refer or relate to aspects of the invention as described below. The descriptions of general meanings of these terms are not intended to be limiting, only illustrative.

1 **base station controller** — in general, a device for performing coordination and
2 control for a wireless communication cell. There is no particular requirement that
3 the base station controller must be a single device; in alternative embodiments, the
4 base station controller can include a portion of a single device, a combination of
5 multiple devices, or some hybrid thereof.

- 6
- 7 • **communication link** — in general, an element for sending information from a
8 sender to a recipient. Although in a preferred embodiment the communication
9 links referred to are generally wireless line of sight point-to-point communication
10 links, there is no particular requirement that they are so restricted.

- 11
- 12 • **customer premises equipment** — in general, a device for performing communi-
13 cation processes and tasks at a customer location, and operating in conjunction
14 with the base station controller within a wireless communication cell. There is no
15 particular requirement that the customer premises equipment must be a single de-
16 vice; in alternative embodiments, the customer premises equipment can include a
17 portion of a single device, a combination of multiple devices, or some hybrid
18 thereof.

- 19
- 20 • **physical parameters** — in general, with reference to a wireless communication
21 link, a set of characteristics or parameters relating to physical transmission of in-
22 formation on a communication link. For example, physical characteristics can in-

1 clude (a) a symbol transmission rate, (b) a number of payload data bits assigned
2 per symbol, (c) a number of error detection or correction bits assigned per symbol,
3 and the like.

- 4 • **wireless communication system** — in general, a communication system including
5 at least one communication link that uses wireless communication techniques.
6
- 7 • **wireless transport layer** — in general, a set of protocols and protocol parameters
8 for sending and receiving information using wireless transport. In a preferred em-
9 bodiment, the wireless transport layer is part of a multilayer systems architecture,
10 in which the wireless transport layer is built using a physical transport layer, and
11 the wireless transport layer is used by a logical transport layer such as IP.

12

13 As noted above, these descriptions of general meanings of these terms are
14 not intended to be limiting, only illustrative. Other and further applications of the inven-
15 tion, including extensions of these terms and concepts, would be clear to those of ordinary
16 skill in the art after perusing this application. These other and further applications are
17 part of the scope and spirit of the invention, and would be clear to those of ordinary skill
18 in the art, without further invention or undue experimentation.

1 *System Context*

2
3 A system using a wireless transport layer in a wireless communication sys-
4 tem operates as part of a system in which devices coupled to a network (such as a com-
5 puter network) send messages, route and switch messages, and receive messages. Most
6 current link layer protocols use a simple “first come, first served” policy for serving these
7 messages. Other systems allow the physical link to be divided into a number of virtual
8 links, each with its own set of bandwidth and QoS parameters. Unlike the existing tech-
9 nology, the device described herein also includes a virtual link that describes a set of
10 physical layer parameters. Thus, in a preferred embodiment, devices coupled to (and in-
11 tegrated with) the network send, route, and receive these messages as sequences of pack-
12 ets, each of which has a header including delivery information and a payload including
13 data. The packet format conforms to the OSI model, in which an application protocol
14 (layer 4, such as TCP) uses a logical transport protocol (layer 3, such as IP), which uses a
15 physical transport protocol (layer 2), which uses a physical transport technique (layer 1).

16
17 The system using a wireless transport layer is described herein with regard
18 to layer 2, particularly as it applies to interactions with layer 1 and layer 3. However,
19 concepts and techniques of the invention are also applicable to other layers of the OSI
20 model. Adapting those concepts and techniques to such other layers would not require
21 undue experimentation or further invention, and is within the scope and spirit of the in-
22 vention.

System Elements

Figure 1 shows a block diagram of a system using a new wireless transport layer in a wireless communication system.

A system 100 includes a wireless communication cell 110, a base station controller 120, and one or more sets of customer premises equipment 130.

The wireless communication cell 110 includes a generally hexagon-shaped region of local surface area, such as might be found in a metropolitan region. Use of generally hexagon-shaped regions is known in the art of wireless communication because they are able to tile a local region with substantially no gaps. However, although in a preferred embodiment the wireless communication cell 110 includes a generally hexagon-shaped region, there is no particular requirement for using that particular shape; in alternative embodiments it may be useful to provide another shape or tiling of the local surface area.

The base station controller 120 includes a processor, program and data memory, mass storage, and one or more antennas for sending or receiving information using wireless communication techniques.

1 Similar to the base station controller 120, each set of customer premises
2 equipment 130 includes a processor, program and data memory, mass storage, and one or
3 more antennas for sending or receiving information using wireless communication tech-
4 niques.

5
6 Communication among devices within the wireless communication cell 110
7 is conducted on one-to-one basis between each set of customer premises equipment 130
8 and the base station controller 120. Thus, the base station controller 120 communicates
9 with each set of customer premises equipment 130, and each set of customer premises
10 equipment 130 communicates with the base station controller 120. Customer premises
11 equipment 130 do not communicate directly with other customer premises equipment
12 130.

13
14 Communication between the base station controller 120 and each set of
15 customer premises equipment 130 is conducted using a time division duplex technique, in
16 which time duration is are divided into individual frames, each one of which includes a
17 “downstream” portion and an “upstream” portion. Unlike existing protocols in which
18 transmissions are controlled by the transmitting side, the base station controller 120 con-
19 trols transmissions for both upstream and downstream directions, without specific requests
20 from the customer premises equipment 130.

1 During the downstream portion of each frame, the base station controller
2 120 transmits, thus sending information to one or more sets of customer premises equip-
3 ment 130. During the upstream portion of each frame, the base station controller auto-
4 matically allocates slots for upstream re-transmission. This occurs in the absence of an
5 explicit request for a slot from the customer premises equipment 130. Particular aspects
6 of each frame are described with regard to figure 2. Time division duplex techniques are
7 known in the art of wireless communication.

8 9 *TDMA Frame*

10
11 Figure 2 shows a timing diagram of a TDMA frame using a new wireless
12 transport layer in a wireless communication system.

13
14 A timing diagram 200 shows a time division multiple access (TDMA)
15 frame 210, including the downstream portion 220 and the upstream portion 230. A guard
16 band 240 separates the downstream portion 220 from the upstream portion 230. In a pre-
17 ferred embodiment, the guard band 240 has a duration at least equal to twice the flight
18 time of a transmission from the base station controller 120 to the most distant customer
19 premises equipment 130 and back.

20
21 Each frame included in a TDMA frame 210 includes a frame descriptor
22 packet 250 that describes the contents of the following frame to each consumer premises

1 equipment 130. The frame descriptor packet 250 has several constant properties: (1) it is
2 always the first packet in a TDMA frame 210; and (2) it is always a fixed size. In addi-
3 tion to these constants, the size of a TDMA frame 210 is also fixed and every TDMA
4 frame always starts at times that are multiples of the frame size. These constant proper-
5 ties ensure that contact between the consumer premises equipment 130 and the base sta-
6 tion controller 120 is always maintained, even if one or more frame descriptor packets
7 230 should get "lost".

8
9 Each frame included in the downstream portion 220 includes a map section
10 221, a synchronization section 222, and one or more downstream payload elements 223,
11 all of which are formatted as data packets, complete with packet headers and associated
12 information. An inter-payload guard band 224 separates successive downstream payload
13 elements 223. In a preferred embodiment, the inter-payload guard band 224 has a dura-
14 tion of sixteen symbols (where the duration of each symbol is responsive to the initial
15 map section 221), but in alternative embodiments, the duration may take on other values.

16
17 Each frame in the upstream portion 230 includes one or more request sec-
18 tions 231, one or more acknowledgment sections 232, a maintenance section 233, and one
19 or more upstream payload elements 223. all of which are formatted as data packets, com-
20 plete with packet headers and associated information. Similar to the downstream portion
21 220, an inter-payload guard band 224 separates successive upstream payload elements
22 223.

1
2 Unlike existing systems that monitor the number of packets that are trans-
3 mitted, the system 100 monitors the number of bytes that are transmitted. Thus, the
4 packet sizes included in the upstream and downstream frames can vary without breaking
5 protocol.

6 The base station controller 120 directs each set of customer premises
7 equipment 130 to conduct wireless communication using a set of physical parameters and
8 a set of MAC parameters, as selected by the base station controller 120. Because each set
9 of customer premises equipment 130 is uniquely situated, the base station controller 120
10 cannot generally determine a single set of physical parameters and MAC parameters to be
11 used by all of the customer premises equipment 130 at once. Accordingly, the base sta-
12 tion controller 120 determines the individual physical parameters and individual MAC
13 parameters to be used by each individual set of customer premises equipment 130. After
14 making each such individual determination, the base station controller 120 constructs a
15 descriptor, for each set of customer premises equipment 130, of physical parameters and
16 MAC parameters to be used by that set of customer premises equipment 130. In a pre-
17 ferred embodiment, this descriptor packet pre-announces the new set of parameters to
18 each transmitter or receiver device, thereby allowing them to configure themselves to the
19 new set of parameters. This is very different from existing schemes which embed the pa-
20 rameters in the header of a packet. Embedding the parameters in the header of a packet
21 causes problems because the header always has to be sent using a common set of pa-

rameters. Moreover, using a packet header in this way does not allow sufficient time for the transmitter or receiver to re-configure itself for the data payload burst.

In a preferred embodiment, the physical parameters and MAC parameters that can be tailored by a base station controller 120 include some or all or a combination of the following:

- Symbol rate
- Modulation
- Power
- Polarization
- Antennae
- Forward Error Correction
- Packet Size

The map section 221 includes, for each set of customer premises equipment 130, the descriptor of physical parameters and MAC parameters to be used by that set of customer premises equipment 130.

The synchronization section 222 is used to synchronize the base station controller 120 clock (not shown) with clocks included in each customer premises equipment 130 (not shown). Each synchronization section 222 includes a set of information (such as an equalizer training sequence) known ahead of time by each set of customer

1 premises equipment 130. Each set of customer premises equipment 130 is capable of re-
2 ceiving the synchronization section 222 (and therefore the known information in the syn-
3 chronization section 222), and capable of synchronizing its internal clock (not shown) to
4 correspond with a master clock (not shown) at the base station controller 120. For exam-
5 ple, each set of customer premises equipment 130 can include a phase locked loop dis-
6 posed so as to receive the synchronization section 222 and phase lock the internal clock
7 for that set of customer premises equipment number 130 with the master clock at the base
8 station controller 120. Thus, each set of customer premises equipment 130 is frequently
9 synchronized with the base station controller 120. Techniques for synchronization of
10 distributed equipment using wireless communication are known in the art of wireless
11 communication.

12
13 Each downstream payload element 223 includes payload information sent
14 from the base station controller 120 to a specific target set of customer premises equip-
15 ment 130. The payload information is separately formatted by the base station controller
16 120 in response to the physical parameters and MAC parameters for the target customer
17 premises equipment 130. Thus, each downstream payload element 223 includes a se-
18 quence of symbols, each encoding a sequence of bits, separately formatted by the base
19 station controller 120, transmitted by the base station controller 120, and thus sent from
20 the base station controller 120 to the target customer premises equipment 130.

1 Those skilled in the art will recognize, after perusal of this application, that
2 each downstream payload element 223 is separately formatted according to an individual
3 set of physical parameters and MAC parameters. Thus, each downstream payload ele-
4 ment 223 might have an individual duration, and even when two downstream payload
5 elements 223 have identical duration, might have an individual number of symbols, an
6 individual number of bits per symbol, and an individual number of total bits for the
7 downstream payload element 223.

8 Those skilled in the art will recognize, after perusal of this application, that
9 each downstream payload element 223 is separately received and decoded by its target
10 customer premises equipment 130, according to the individual set of physical parameters
11 and MAC parameters determined by the base station controller 120 and sent by the base
12 station controller 120 during the map section 221 in the same downstream portion 220 in
13 the same TDMA frame 210. Thus, the base station controller 120 is able to send infor-
14 mation to each set of customer premises equipment 130 and to direct each set of customer
15 premises equipment 130 to receive that information using an optimal set of physical pa-
16 rameters and MAC parameters for that TDMA frame 210.

17
18 Similarly, the base station controller 120 directs each set of customer
19 premises equipment 130 to conduct communications using the physical parameters and
20 MAC parameters transmitted in the map section 221 of the same TDMA frame 210.
21 Thus, upstream payload elements 223 sent by each individual set of customer premises
22 equipment 130 are formatted by each individual set of customer premises equipment 130

1 using the optimal set of physical parameters and MAC parameters (as determined by the
2 base station controller 120) for that TDMA frame 210.

3
4 The request section 231 includes a sequence of requests to transmit up-
5 stream payload elements 223, as requested by each set of customer premises equipment
6 130. The request section 231 is not expressed as a unit of time or a number of packets.
7 The request section 231 specifically requests a number of payload bytes. This is prefer-
8 able since given that the packets are of variable size, specifying their number does not tell
9 the base station controller 120 about the number of bytes that need to be transmitted.
10 Furthermore, it is not feasible for the consumer premises equipment 130 to make requests
11 in units of transmit time because the link parameters assigned to the consumer premises
12 equipment 130 change over time. The consumer premises equipment 130 sequentially
13 numbers each byte and writes the sequence number of the last byte in its buffer into the
14 request section 231. In combination with the sequence number of the byte being trans-
15 mitted, this scheme allows the base station controller 120 to unambiguously estimate the
16 current backlog in the consumer premises equipment 130.

17
18 The acknowledgment sections 232 each include an acknowledgment mes-
19 sage by customer premises equipment 130 not otherwise sending an acknowledgment to
20 the base station controller 120.

1 The maintenance section 233 includes maintenance information transmitted
2 by either the base station controller 120 or by one or more sets of customer premises
3 equipment 130.

4
5 Similar to the downstream payload elements 223, the upstream payload
6 elements 223 each includes payload information sent from customer premises equipment
7 130 to the base station controller 120. The payload information is separately formatted by
8 each customer premises equipment 130 in response to the physical parameters and MAC
9 parameters determined by the base station controller 120 for the sending customer prem-
10 ises equipment 130 (and transmitted during the map section 221). Thus, similar to each
11 downstream payload element 223, each upstream payload element 223 includes a se-
12 quence of symbols, each encoding a sequence of bits, separately formatted by the cus-
13 tomer premises equipment 130, transmitted by the customer premises equipment 130, and
14 thus sent from the customer premises equipment 130 to the base station controller 120.

15 16 *Method of Operation*

17
18 Figure 3 shows a process flow diagram of a method for operating a system
19 using a new wireless transport layer in a wireless communication system.

20
21 A method 300 includes a set of flow points and a set of steps. The system
22 100 performs the method 300. Although the method 300 is described serially, the steps of

1 the method 300 can be performed by separate elements in conjunction or in parallel,
2 whether asynchronously, in a pipelined manner, or otherwise. There is no particular re-
3 quirement that the method 300 be performed in the same order in which this description
4 lists the steps, except where so indicated.

5 6 Sending Downstream Information

7
8 At a flow point 310, the base station controller 120 is ready to send infor-
9 mation to one or more sets of customer premises equipment 130.

10
11 At a step 311, the base station controller 120 determines sets of physical pa-
12 rameters and MAC parameters it considers optimal for each set of customer premises
13 equipment 130.

14
15 At a step 312, the base station controller 120 determines information it will
16 send to each set of customer premises equipment 130.

17
18 At a step 313, the base station controller 120 formats the downstream por-
19 tion 220 of the TDMA frame 210. As part of this step, the base station controller 120
20 formats the map section 221, to include the physical parameters and MAC parameters it
21 determined in the step 311 for each individual set of customer premises equipment 130.
22 As part of this step, the base station controller 120 formats the synchronization section

222. As part of this step, the base station controller 120 formats one or more downstream payload elements 223, to include the information it determined in the step 312 for each individual set of customer premises equipment 130.

At a step 314, the base station controller 120 waits for the guard band 340 to pass before attempting to receive information from customer premises equipment 130. The method 300 continues with the flow point 330 and the flow point 340.

After this step, the base station controller 120 has performed one instance of sending information during the downstream portion 220. The flow point 310 is reached repeatedly and the steps thereafter are performed repeatedly, for each TDMA frame 210.

Receiving Downstream Information

At a flow point 320, preferably reached in parallel with the flow point 310, one or more sets of customer premises equipment 130 are ready to receive information from the base station controller 120.

At a step 321, each individual customer premises equipment 130, having been earlier synchronized with the base station controller 120, receives the map section 221, including the physical parameters and MAC parameters the base station controller

120 considers optimal for communication with that individual of customer premises equipment 130.

At a step 322, each individual customer premises equipment 130 receives the synchronization section 222, and re-synchronizes its internal clock to correspond with the master clock at the base station controller 120. Since each individual customer premises equipment 130 can be a different distance from the base station controller 120, each individual customer premises equipment 130 will receive the synchronization section 222 at a (slightly) different time, and thus each individual customer premises equipment 130 will run its internal clock at a (slightly) different phase from the master clock at the base station controller 120.

At a step 323, each individual customer premises equipment 130 receives one or more downstream payload elements 223, using the physical parameters and MAC parameters it received during the map section 221.

At a step 324, each individual customer premises equipment 130 waits for the guard band 340 to pass before attempting to send information to the base station controller 120. The method 300 continues with the flow point 330 and the flow point 340.

After this step, each individual customer premises equipment 130 has performed one instance of receiving information during the downstream portion 220. The

1 flow point 320 is reached repeatedly and the steps thereafter are performed repeatedly, for
2 each TDMA frame 210.

3
4 Sending Upstream Information

5
6 At a flow point 330, individual customer premises equipment 130 are ready
7 to send information to the base station controller 120.

8
9 At a step 331, each individual customer premises equipment 130 determines
10 whether it desires to request allocation of bandwidth for transmission during the TDMA
11 frame 210. As part of this step, the individual customer premises equipment 130 formats
12 a request for transmission during a specific request section 231 designated for use by that
13 individual customer premises equipment 130.

14
15 At a step 332, each individual customer premises equipment 130 that de-
16 sires to request allocation of bandwidth for transmission transmits during its assigned re-
17 quest section 231, so as to inform the base station controller 120 of its desire. For exam-
18 ple, individual customer premises equipment 130 might be given a numeric ordering by
19 the base station controller 120, so that each individual customer premises equipment 130
20 has an assigned time slot during which it can request bandwidth allocation from the base
21 station controller 120. Alternatively, individual customer premises equipment 130 might

1 contend for individual request sections 231, using a “slotted aloha” technique or other
2 known technique for contention for limited resources.

3
4 In a alternative embodiment, the base station controller 120 determines, for
5 each request section 231, whether that request section 231 will be assigned to a particular
6 customer premises equipment 130, or will be open for contention like multiple customer
7 premises equipment 130. In the latter case, the base station controller 120 determines, for
8 those request sections 231 which are open for contention, whether contention will be lim-
9 ited to particular subsets of customer premises equipment 130, or whether contention will
10 be open to all customer premises equipment 130.

11
12 When the base station controller 120 receives requests for allocation of
13 bandwidth, the base station controller 120 determines, for the following TDMA frame
14 210, the allocations of bandwidth it considers optimal for particular customer premises
15 equipment 130. The particular allocations determined by the base station controller 120
16 are transmitted during the next TDMA frame 210, during the downstream portion 220,
17 during the map section 221.

18
19 At a step 333, each individual customer premises equipment 130 that de-
20 sires to make an acknowledgment of information is received from the base station con-
21 troller 120, transmits during its designed acknowledgment section 232, so as to inform the
22 base station controller 120 of its acknowledgment. In a preferred embodiment, acknowl-

1 edgment sections 232 are specifically assigned to individual customer premises equip-
2 ment 130.

3
4 In an alternative embodiment, the base station controller 120 determines,
5 for each acknowledgment section 232, which particular customer premises equipment 130
6 will have use of that acknowledgment section 232. Moreover, in a preferred embodiment,
7 individual customer premises equipment 130 having allocations of bandwidth for trans-
8 mission using upstream payload elements 223 will generally not require further band-
9 width for transmission during acknowledgments sections 232. Accordingly, the base sta-
10 tion controller 120 can reserve individual acknowledgment sections 232 for particular
11 customer premises equipment 130 not already having allocations for bandwidth for
12 transmission using upstream payload elements 223.

13
14 At a step 334, each individual customer premises equipment 130 determines
15 whether it needs to transmit during the maintenance section 233. As part of this step,
16 each individual customer premises equipment 130 which has so determined formats in-
17 formation for transmission during the maintenance action 233, and transmits that infor-
18 mation during the maintenance section 233, so that the base station controller 120 can re-
19 ceive that information.

20
21 At a step 335, each individual customer premises equipment 130 heading
22 allocations of bandwidth for transmission using upstream payload elements 223 deter-

1 mines what information that individual customer premises equipment intends to send to
2 the base station controller 120. As part of this step, each individual customer premises
3 equipment 130, intending to send information to the base station controller 120, formats
4 information into an upstream payload element 223, and transmits that upstream payload
5 element 223 during the time assigned for transmission to that individual cost of premises
6 equipment 130.

7
8 In a preferred embodiment, the base station controller 120 determines, for
9 each time slot possibly allocable for an upstream payload element 223, which specific in-
10 dividual customer premises equipment 130 is allocated that particular time slot. How-
11 ever, in alternative embodiments, the base station controller 120 might reserve one or
12 more time slots allocable for upstream payload elements 223 for contention among more
13 than one individual customer premises equipment 130.

14
15 As noted above, each individual customer premises equipment 130 uses the
16 physical parameters and MAC parameters determined by the base station controller 120
17 for that particular customer premises equipment 130 and transmitted during the map sec-
18 tion 221 of the same TDMA frame 210.

19
20 After this step, each individual customer premises equipment 130 has per-
21 formed one instance of sending information during the upstream portion 230. The flow

point 330 is reached repeatedly and the steps thereafter are performed repeatedly, for each TDMA frame 210.

Receiving Upstream Information

At a flow point 340, preferably reached in parallel with the flow point 330, the base station controller 120 is ready to receive information from one or more sets of customer premises equipment 130.

At a step 341, the base station controller 120 receives information transmitted during each request section 231 by one or more individual customer premises equipment 130. As part of this step, the base station controller 120 determines whether one or more request sections 231 have been subject to contention (and thus have been unable to be used to send or receive information). As part of this step, the base station controller 120 determines what allocations of bandwidth for transmission it will make for individual customer premises equipment 130 for the following TDMA frame 210.

At a step 342, the base station controller 120 receives information transmitted during each acknowledgment section 232, by one or more individual customer premises equipment 130. As part of this step, the base station controller 120 determines which of its downstream payload elements 223 sent to individual customer premises equipment 130 have been acknowledged and therefore have been received properly.

1
2 At a step 343, the base station controller 120 receives information trans-
3 mitted during the maintenance section 233, by one or more individual customer premises
4 equipment 130. As part of this step, the base station controller 120 determines any main-
5 tenance steps it must take in response to such information.

6
7 At a step 344, the base station controller 120 receives information trans-
8 mitted during one or more upstream payload elements 223, by one or more individual
9 customer premises equipment 130. As part of this step, similar to receipt of individual
10 request sections 231 (and possibly similar to receipt of individual acknowledgment sec-
11 tions 232), the base station controller 120 determines whether one or more upstream pay-
12 load elements 223 have been subject to contention (and thus have been unable to be used
13 to send or receive information).

14
15 In a alternative embodiment, the base station controller 120 parses those up-
16 stream payload elements 223 for which it has been able to receive information, and de-
17 termines whether those upstream payload elements 223 include acknowledgments of
18 downstream payload elements 223 which were sent by the base station controller 122 to
19 individual customer premises equipment 130. If so, the base station controller 120 treats
20 those acknowledgments which were “piggybacked” onto upstream payload elements 223
21 in similar manner to acknowledgments received during acknowledgment sections 232.

1 As noted above, the base station controller 120 receives and parses those
2 upstream payload elements 223 using physical parameters and MAC parameters deter-
3 mined by the base station controller 120 for that particular customer premises equipment
4 130 and transmitted during the map section 221 of the same TDMA frame 210.

5
6 After this step, the base station controller 120 has performed one instance of
7 receiving information during the upstream portion 230. The flow point 340 is reached
8 repeatedly and the steps thereafter are performed repeatedly, for each TDMA frame 210.

9
10 An optional step 345 may occur at any time during the method 300 in re-
11 sponse to the frequency of dropped packets. A packet is designated as “dropped” after
12 the method 300 failed to get it across after re-transmitting it several times. In this step,
13 the system 100 changes link parameters if two packets are dropped within a specified
14 number of packet transmissions from each other. This allows the system 100 to tolerate a
15 certain level of dropped packets without being affected. However, if the drop rate ex-
16 ceeds a certain threshold, the link parameters are changed. This approach is very differ-
17 ent from existing methods which change link parameters in response to explicit measure-
18 ments such as the signal-to-interference ratio.

Generality of the Invention

The invention has general applicability to various fields of use, not necessarily related to the services described above. For example, these fields of use can include one or more of, or some combination of, the following:

The invention is applicable to other forms of wireless communication, such as frequency division multiple access (FDMA) or code division multiple access (CDMA, also known as spread spectrum communication);

- The invention is applicable to wireline (that is, non-wireless) communication, in which now can be achieved from dynamically adjusting communication parameters, such as physical parameters or MAC parameters. For example, the invention can be generalized to wireline communication using modems in which equalization parameters are to be dynamically adjusted.

The invention is applicable to other wireless communication systems, such as satellite communication systems and (microwave tower or other) point to point transmission systems.

1 Other and further applications of the invention in its most general form, will
2 be clear to those skilled in the art after perusal of this application, and are within the
3 scope and spirit of the invention.

4
5 *Technical Appendix*

6
7 A technical appendix enclosed with this application is part of the disclosure
8 of this application, and is hereby incorporated by reference as if fully set forth herein.

9
10 *Alternative Embodiments*

11
12 Although preferred embodiments are disclosed herein, many variations are
13 possible which remain within the concept, scope, and spirit of the invention, and these
14 variations would become clear to those skilled in the art after perusal of this application.